



Hire Details

Hire of this item includes:

X1 Alesis MultiMix 8

X1 Aluminium Case

X1 External Power Supply

**You must specify when ordering if you require any XLR Cables*

Alesis MultiMix 8 Specifications

General

- Console Type: Analog Mixer with Built-in Effects and USB Interface
- Mixer Configuration: 8-Channel

Audio Inputs

- Microphone Inputs: 4 x XLR (with switchable phantom power)
- Line Inputs: 4 x 1/4" TRS (balanced/unbalanced), 2 x stereo pairs (1/4" TRS)
- Auxiliary Inputs: 2-Track RCA (stereo)
- Instrument Inputs: 1 x Hi-Z (switchable for direct connection of guitar/bass)
- Insert Points: 2 x 1/4" TRS (on channels 1 and 2)

Audio Outputs

- Main Outputs: 2 x 1/4" TRS (left/right)
- Auxiliary Sends: 1 x 1/4" TRS (pre/post switchable)
- Control Room Outputs: 2 x 1/4" TRS
- Headphone Output: 1 x 1/4" TRS stereo
- 2-Track Output: RCA (stereo)

Control and Processing

- Faders: 60mm master fader
- EQ: 3-band EQ with sweepable midrange on mono channels, 3-band fixed EQ on stereo channels
- Auxiliary Sends: 1 auxiliary send per channel
- Effects: Built-in DSP effects processor with 100 presets (including reverb, delay, chorus, and more)
- Phantom Power: +48V globally switched

USB Interface

- USB Audio: Stereo output to computer via USB (16-bit, 44.1/48 kHz)
- Compatibility: Works with Windows and macOS without special drivers

Monitoring and Metering

- LED Meters: 4-segment stereo LED meters
- PFL/Solo: Solo button on each channel for monitoring

Physical

- Dimensions: 12.4" x 9.6" x 2.4" (315 x 245 x 61 mm)
- Weight: 4.9 lbs (2.2 kg)

Power

- Power Supply: External power adapter
- Voltage: 18V, 500mA